

Amended claims

I claim:

1-25 (Cancelled)

26) (Currently Amended) An electronic circuit for adding reverberation effects to an audio signal generated from an external high impedance source and passing the reverberated signal at a predetermined impedance for input into an external sound device, said electronic circuit comprising, in combination:

(a) a reverberation effects circuit having pre-amplifier/driver and recovery amplifier sections and a spring reverberation device coupled thereinbetween, said pre-amplifier/driver section having an input jack for receiving therethrough a high impedance signal produced from an external audio source, a DC isolation filter, and a low impedance, high current output for input into said spring reverberation device having an output for passing a low impedance signal to said recovery amplifier section for increasing the impedance of the signal to a level acceptable for input into the external sound device, said spring reverberation device employs three springs with each of said springs having a first spring end and a second spring end and each of the three first spring ends connected to a single first spring end connecting bar, and each of the three second spring ends connected a second spring end connecting bar, said pre-amplifier/driver section comprises first and second operational amplifiers each having inverting and non-inverting inputs and an output, each of said outputs comprising a negative feedback loop coupled to said inverting inputs and shunted to ground for setting a predetermined gain value at said output, The electronic circuit as set forth in claim 25, wherein said first operational amplifier comprises a switch at said non-inverting input for controlling the audio signal path through said reverberation effects circuit and a path to ground comprising resistive capacity for maintaining an impedance level into said first operational amplifier and keeping the audio source from being loaded.

27) (Cancelled)

28) (Currently Amended) An electronic circuit for adding reverberation effects to an audio signal generated from an external high impedance source and passing the reverberated signal at a predetermined impedance for input into an external sound device, said electronic circuit comprising, in combination:

Amended claims

(a) a reverberation effects circuit having pre-amplifier/driver and recovery amplifier sections and a spring reverberation device coupled thereinbetween, said pre-amplifier/driver section having an input jack for receiving therethrough a high impedance signal produced from an external audio source, a DC isolation filter, and a low impedance, high current output for input into said spring reverberation device having an output for passing a low impedance signal to said recovery amplifier section for increasing the impedance of the signal to a level acceptable for input into the external sound device, said spring reverberation device employs three springs with each of said springs having a first spring end and a second spring end and each of the three first spring ends connected to a single first spring end connecting bar, and each of the three second spring ends connected to a second spring end connecting bar, said pre-amplifier/driver section comprises first and second operational amplifiers each having inverting and non-inverting inputs and an output, each of said outputs comprising a negative feedback loop coupled to said inverting inputs and shunted to ground for setting a predetermined gain value at said output, The electronic circuit as set forth in claim 25, wherein said output of said first operational amplifier is coupled to said non-inverting input of said second operational amplifier, said input comprising a filter for blocking passage of dc signals while allowing passage of the audio signal into said second operational amplifier, said negative feedback loop of said second operational amplifier comprising a resistor/capacitor arrangement for stabilizing said feedback loop and restoring phase margin to said second operational amplifier.

29) (Cancelled)

30) (Currently Amended) An electronic circuit for adding reverberation effects to an audio signal generated from an external high impedance source and passing the reverberated signal at a predetermined impedance for input into an external sound device, said electronic circuit comprising, in combination:

(a) a reverberation effects circuit having pre-amplifier/driver and recovery amplifier sections and a spring reverberation device coupled thereinbetween, said pre-amplifier/driver section having an input jack for receiving therethrough a high impedance signal produced from an external audio source, a DC isolation filter, and a low impedance, high current output for input into said spring reverberation device having an

output for passing a low impedance signal to said recovery amplifier section for increasing the impedance of the signal to a level acceptable for input into the external sound device, said spring reverberation device employs three springs with each of said springs having a first spring end and a second spring end and each of the three first spring ends connected to a single first spring end connecting bar, and each of the three second spring ends connected a second spring end connecting bar. ~~The electronic circuit as set forth in claim 23, wherein~~ said recovery amplifier section comprises a single operational amplifier having an inverting input for receiving a reverberated signal from said reverberation device, a non-inverting input shunted to ground and an output comprising a negative feedback loop coupled to said inverting input for setting the reverberated signal at a predetermined gain and impedance for input into the external sound device.

31) (Currently Amended) The electronic circuit as set forth in claim 30, wherein said negative feedback loop of said single operational amplifier comprises a 50K-linear potentiometer having variable resistive capacity to variably adjust gain and establish a predetermined impedance of the signal at said output suitable for input into the external sound device.

32) (Cancelled)

33) (Previously Presented) A method for adding reverberation effects to an audio signal generated from an external high impedance device and passing the reverberated signal at a predetermined impedance for input into an external sound device, said method comprising the steps of:

- (a) sending the audio signal into an non-inverting input of a first operational amplifier having an inverting input shunted to ground and an output comprising a negative feedback loop coupled to said inverting input for setting a predetermined gain value and impedance at said output prior to being coupled to a non-inverting input of a second operational amplifier having an inverting input shunted to ground and a low impedance, high current output for input into a spring reverberation device having an output for passing therethrough a reverberated signal;
- (b) passing the audio signal through a DC-Isolation filter.
- (c) passing the reverberated signal into an inverting input of a single operational amplifier having a non-inverting input shunted to ground and an output having a negative feedback

Amended claims

loop coupled to said inverting input for setting a predetermined gain and impedance acceptable for input into the external sound device.

34) (Previously Presented) The method of claim 33 wherein the spring reverberation device comprises three springs with each of said springs having a first spring end and a second spring end and each of the three first spring ends connected to a single first spring end connecting bar, and each of the three second spring ends connected a second spring end connecting bar.

35) (Previously Presented) A method as set forth in claim 34, wherein said negative feedback loop of said first operational amplifier comprises a ~~50K~~-linear potentiometer having variable resistive capacity to variably adjust gain of the signal and establish low impedance at said output of said first operational amplifier.

36) (Previously Presented) A method as set forth in claim 34, wherein said negative feedback loop of said second operational amplifier comprises a resistor/capacitor arrangement for stabilizing said feedback loop and restoring phase margin to said second operational amplifier.

37) (Previously Presented) A method as set forth in claim 34, further comprising the step of coupling a switch at said non-inverting input of said first operational amplifier for controlling the addition of reverberation to the audio signal and a reverberation effects bypass prior to said switch for maintaining the integrity and impedance of the audio signal for direct input into the external sound device.

38) (Currently Amended) An electronic circuit for adding reverberation effects to an audio signal generated from an external high impedance source and passing the reverberated signal at a predetermined impedance for input into an external sound device, said electronic circuit comprising, in combination:

(a) first and second operational amplifiers each having inverting and non-inverting inputs and an output, each of said outputs comprising a negative feedback loop coupled to said inverting inputs and shunted to ground, said negative feedback loop of said first operational amplifier comprising a ~~50K~~ linear potentiometer having variable resistive capacity to variably adjust gain of the signal and establish low impedance at said output of said first operational amplifier, said negative feedback loop of said second operational

Amended claims

amplifier comprising a resistor/capacitor arrangement for stabilizing said feedback loop and restoring phase margin to said second operational amplifier;

(b) a DC Isolation filter interposed between said first and said second operational amplifiers;

(c) a spring reverberation device having an input for accepting a low impedance, high current signal from said output of second operational amplifier and an output for passing therethrough a reverberated signal; and

(d) a single operational amplifier having a non-inverting input shunted to ground and an output having a negative feedback loop coupled to said inverting input for setting a predetermined gain and impedance acceptable for input into the external sound device.

39) (Previously Presented) The electronic circuit of claim 38 wherein the spring reverberation device employs three springs with each of said springs having a first spring end and a second spring end and each of the three first spring ends connected to a single first spring end connecting bar, and each of the three second spring ends connected a second spring end connecting bar.

40) (Currently Amended) The electronic circuit as set forth in claim 39, wherein said negative feedback loops of said first and single operational amplifiers each comprise a ~~50K~~ linear potentiometer having variable resistive capacity to variably adjust gain of the signal and a predetermined impedance at said outputs of said first and second operational amplifiers.

41) (Previously Presented) The electronic circuit as set forth in claim 39, wherein said negative feedback loop of said second operational amplifier comprises a resistor/capacitor arrangement for stabilizing said feedback loop and restoring phase margin to said second operational amplifier.

42) (Previously Presented) The electronic circuit as set forth in claim 39, wherein said output from said single operational amplifier comprises a capacitive capacity to filter voltage spikes prior to passing the signal to the external sound device and a path to ground having resistive capacity to reinforce the impedance of the signal from said single operational amplifier to match the impedance with that of the external sound device.

POWER OF ATTORNEY and CORRESPONDENCE ADDRESS INDICATION FORM

Application Number	10/757833
Filing Date	January 14, 2004
First Named Inventor	Van Tassel, Timothy Dale
Title	electronic circuit with spring ...
Art Unit	2615
Examiner Name	Disler, Paul
Attorney Docket Number	20071129-001


I hereby revoke all previous powers of attorney given in the above-identified application.

I hereby appoint:

☐ Practitioners associated with the Customer Number:

OR

☒ Practitioner(s) named below:



Name	Registration Number
Roger L. Belfay	51449

as my/our attorney(s) or agent(s) to prosecute the application identified above, and to transact all business in the United States Patent and Trademark Office connected therewith.

Please recognize or change the correspondence address for the above-identified application to:

☐ The address associated with the above-mentioned Customer Number:

OR

☐ The address associated with Customer Number:

OR

<input checked="" type="checkbox"/> Firm or Individual Name	Roger L. Belfay				
Address	829 Tuscarora Avenue				
City	Saint Paul	State	MN	Zip	55102
Country	USA				
Telephone	651-222-2782	Email	rogerbelfay@rogerbelfay.com		

I am the:

☒ Applicant/Inventor.

☐ Assignee of record of the entire interest. See 37 CFR 3.71.
Statement under 37 CFR 3.73(b) is enclosed. (Form PTO/SB/96)

SIGNATURE of Applicant or Assignee of Record

Signature	<i>Timothy Dale Van Tassel</i>	Date	12/18/07
Name	Timothy Dale Van Tassel	Telephone	763-529-1206
Title and Company	Inventor		

NOTE: Signatures of all the inventors or assignees of record of the entire interest or their representative(s) are required. Submit multiple forms if more than one signature is required, see below.

☒ *Total of 1 forms are submitted.

This collection of information is required by 37 CFR 1.31, 1.32 and 1.33. The information is required to obtain or retain a benefit by the public which is to file (and by the USPTO to process) an application. Confidentiality is governed by 35 U.S.C. 122 and 37 CFR 1.11 and 1.14. This collection is estimated to take 3 minutes to complete, including gathering, preparing, and submitting the completed application form to the USPTO. Time will vary depending upon the individual case. Any comments on the amount of time you require to complete this form and/or suggestions for reducing this burden, should be sent to the Chief Information Officer, U.S. Patent and Trademark Office, U.S. Department of Commerce, P.O. Box 1450, Alexandria, VA 22313-1450. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Commissioner for Patents, P.O. Box 1450, Alexandria, VA 22313-1450.

If you need assistance in completing the form, call 1-800-PTO-9199 and select option 2.